

A System Integration Solution

Introducing a new adapter kit, the **MPS-SMBB-KIT-35**. This adapter kit is designed to be installed into a 4" dry wall, between 2 studs and fit flush with the surface of the wall. Designed to accept our wide range of modular panels, be adjustable to accommodate variations in stud placement and provide easy cable access via conduit installed in the top and bottom of the rear enclosure.



Each kit includes a Rear Enclosure / Back Box, a 16MU Flush Mount Ring, and a pair of Label Strips and mounting hardware. The Rear Enclosure, End Caps and Back Box, are designed to adjustable from 14" to 15½" to accommodate variations between studs. The top and bottom of the Back Box is free of any obstructions for the termination of conduit(s) to suite the installation.



Mounting holes are provided in each End Cap to anchor the Rear Enclosure to the studs. Ideally, the Rear Enclosure /Back Box should be installed during construction, mounted between a pair of studs, with conduit run to it before the sheet-rock is installed.



Alternately, the Rear Enclosure / Back Box can be mounted in an existing 4" or deeper wall using the supplied template to mark the cutout in the sheet-rock plus the mounting instructions on how to install it.

A 6" deep version is available for deeper walls. (Part # MPS-SMBB-16MU-6-KIT)

Email your request, or download the AutoCAD drawing from our website to do your own layout using the embedded blocks for all our enclosures and adapters, plus the wide selection of MPS modular panels.

Visit our Website – www.signt.com – or give us a call at (714) 641-5665 for information and pricing on all of our products. Thanks.